



Dialogic® PowerMedia™ XMS RESTful Management API

User's Guide

Copyright and Legal Notice

Copyright © 2012-2016 Dialogic Corporation. All Rights Reserved. You may not reproduce this document in whole or in part without permission in writing from Dialogic Corporation at the address provided below.

All contents of this document are furnished for informational use only and are subject to change without notice and do not represent a commitment on the part of Dialogic Corporation and its affiliates or subsidiaries ("Dialogic"). Reasonable effort is made to ensure the accuracy of the information contained in the document. However, Dialogic does not warrant the accuracy of this information and cannot accept responsibility for errors, inaccuracies or omissions that may be contained in this document.

INFORMATION IN THIS DOCUMENT IS PROVIDED IN CONNECTION WITH DIALOGIC® PRODUCTS. NO LICENSE, EXPRESS OR IMPLIED, BY ESTOPPEL OR OTHERWISE, TO ANY INTELLECTUAL PROPERTY RIGHTS IS GRANTED BY THIS DOCUMENT. EXCEPT AS PROVIDED IN A SIGNED AGREEMENT BETWEEN YOU AND DIALOGIC, DIALOGIC ASSUMES NO LIABILITY WHATSOEVER, AND DIALOGIC DISCLAIMS ANY EXPRESS OR IMPLIED WARRANTY, RELATING TO SALE AND/OR USE OF DIALOGIC PRODUCTS INCLUDING LIABILITY OR WARRANTIES RELATING TO FITNESS FOR A PARTICULAR PURPOSE, MERCHANTABILITY, OR INFRINGEMENT OF ANY INTELLECTUAL PROPERTY RIGHT OF A THIRD PARTY.

Dialogic products are not intended for use in certain safety-affecting situations. Please see <http://www.dialogic.com/company/terms-of-use.aspx> for more details.

Due to differing national regulations and approval requirements, certain Dialogic products may be suitable for use only in specific countries, and thus may not function properly in other countries. You are responsible for ensuring that your use of such products occurs only in the countries where such use is suitable. For information on specific products, contact Dialogic Corporation at the address indicated below or on the web at www.dialogic.com.

It is possible that the use or implementation of any one of the concepts, applications, or ideas described in this document, in marketing collateral produced by or on web pages maintained by Dialogic may infringe one or more patents or other intellectual property rights owned by third parties. Dialogic does not provide any intellectual property licenses with the sale of Dialogic products other than a license to use such product in accordance with intellectual property owned or validly licensed by Dialogic and no such licenses are provided except pursuant to a signed agreement with Dialogic. More detailed information about such intellectual property is available from Dialogic's legal department at 6700 Cote-de-Liesse Road, Suite 100, Borough of Saint-Laurent, Montreal, Quebec, Canada H4T 2B5. **Dialogic encourages all users of its products to procure all necessary intellectual property licenses required to implement any concepts or applications and does not condone or encourage any intellectual property infringement and disclaims any responsibility related thereto. These intellectual property licenses may differ from country to country and it is the responsibility of those who develop the concepts or applications to be aware of and comply with different national license requirements.**

Dialogic, Dialogic Pro, Dialogic Blue, Veraz, Brooktrout, Diva, BorderNet, PowerMedia, PowerVille, PowerNova, MSaaS, ControlSwitch, I-Gate, Mobile Experience Matters, Network Fuel, Video is the New Voice, Making Innovation Thrive, Diastar, Cantata, TruFax, SwitchKit, Eiconcard, NMS Communications, SIPcontrol, Exnet, EXS, Vision, inCloud9, NaturalAccess and Shiva, among others as well as related logos, are either registered trademarks or trademarks of Dialogic Corporation and its affiliates or subsidiaries. Dialogic's trademarks may be used publicly only with permission from Dialogic. Such permission may only be granted by Dialogic's legal department at 6700 Cote-de-Liesse Road, Suite 100, Borough of Saint-Laurent, Montreal, Quebec, Canada H4T 2B5. Any authorized use of Dialogic's trademarks will be subject to full respect of the trademark guidelines published by Dialogic from time to time and any use of Dialogic's trademarks requires proper acknowledgement.

The names of actual companies and products mentioned herein are the trademarks of their respective owners.

This document discusses one or more open source products, systems and/or releases. Dialogic is not responsible for your decision to use open source in connection with Dialogic products (including without limitation those referred to herein), nor is Dialogic responsible for any present or future effects such usage might have, including without limitation effects on your products, your business, or your intellectual property rights.

Table of Contents

1. Welcome	7
2. Overview.....	8
3. Firefox RESTClient Utility	9
Accessing RESTClient.....	9
4. Configuring and Using the RESTClient Utility	10
Using GET with the RESTClient.....	10
Using PUT with the RESTClient.....	11
Using POST with the RESTClient.....	11
Using DELETE with the RESTClient.....	12
5. RESTful Management API Resources.....	13
6. List of Available Resources	17
/system	17
/system/info	18
/system/time	18
/system/backup	20
/system/restore	21
/system/upgrade.....	22
/system/nfsmount	23
/sip.....	24
/rtp	25
/trust.....	26
/httpclient	27
/services	27
/logs.....	31
/logs/process	31
/logs/mediasubsystem	34
/license	37
/codecs	41
/routing	45
/msml.....	46
/media	49
/tones.....	52
/network	58
/network/interface.....	59
/network/dns	60
/mrcpclient.....	61
/mrcpclient/global	62
/mrcpclient/speechserver_sample	63
/mrcpclient/speechserver_speechserver1	64
/netann.....	64
/netann/global	65
/netann/conference	66
/resource	66
/resource/active.....	67
/resource/groups.....	67
/resource/licenses	68

/snmp.....	68
/snmp/trap-destinations.....	69
/snmp/v2c-communities.....	70
/snmp/v3-users	71
/snmp/thresholds	72
/vxml.....	73
/vxml/vxmlinterpreter.....	73
/xmsrest	74
/xmsrest/general.....	75
/xmsrest/trusted	76
/msrp	76
/msrp/global.....	77

Revision History

Revision	Release Date	Notes
05-2711-007 (Updated)	May 2016	Updates to remove legacy MSML mode.
05-2711-007	March 2016	Updates to support PowerMedia XMS 3.0. Removed content throughout the document regarding legacy MSML mode and native mode.
05-2711-006	February 2015	Updates to support PowerMedia XMS Release 2.4. List of Available Resources: Updated /license section.
05-2711-005	October 2014	Updates to support PowerMedia XMS Release 2.3. RESTful Management API Resources : - Updated list of supported resources. List of Available Resources: - Updated /system/time section with zone and zone_offset parameters under Response Payload tables. - Updated /network/interface section. - Updated /mrcpclient, /mrcpclient/global, /mrcpclient/speechserver_sample, and /mrcpclient/speechserver_speechserver1 sections. - Updated /resource/licenses section. - Added /snmp, /snmp/trap-destinations, /snmp/v2c-communities, /snmp/v3-users, and /snmp/thresholds sections. - Updated /xmsrest/general section. - Added /msrp and /msrp/global sections.

Revision	Release Date	Notes
05-2711-004	April 2014	RESTful Management API Resources: - Updated list of supported resources. List of Available Resources: - Added /logs, /logs/process, and /logs/mediasubstream. - Added /netann, /netann/global, and /netann/conference. - Added /resource, /resource/active, /resource/groups, and /resource/licenses.
05-2711-003	February 2014	Updates to support PowerMedia XMS Release 2.2.
05-2711-002	October 2013	Updates to support PowerMedia XMS Release 2.1.
05-2711-001	January 2013	Updates to support PowerMedia XMS Release 2.0. RESTful Management API Resources: Added the RESTful Management API Resources.
05-2711-001-01	October 2012	Initial release of this document.
Last modified: May 2016		

Refer to www.dialogic.com for product updates and for information about support policies, warranty information, and service offerings.

1. Welcome

The Dialogic® PowerMedia™ Extended Media Server (also referred to herein as "PowerMedia XMS" or "XMS") RESTful Management API provides an alternate way of performing system management tasks. Although the PowerMedia XMS is usually configured and managed through an interactive web-based GUI, there may be circumstances where system management could be done in a more automated or distributed manner.

This User's Guide provides instructions for using the RESTful Management API.

2. Overview

The RESTful Management API is used to control the OA&M functions of PowerMedia XMS. Normally, this is done through a GUI, running on a client web browser. However, there may be a need to customize system management functionality, or merge it in with other system management tools in use. The RESTful Management API can be used to accomplish this.

The RESTful Management API uses HTTP or secure HTTPS as its transport so that information about the PowerMedia XMS server configuration cannot be intercepted. In the RESTful Management API, the four HTTP methods are translated to the actions shown in the following table.

HTTP Method	Action
POST	Add a new resource
PUT	Modify an existing resource
GET	Return information about a resource
DELETE	Remove a resource

Request and response payloads must be specified using JavaScript Object Notation (JSON). JSON is a lightweight data-interchange format based on a subset of the JavaScript Programming Language, Standard ECMA-262 3rd Edition - December 1999. JSON is a text format that is completely language independent but uses conventions that are familiar to programmers of the C-family of languages, including Java, JavaScript, Perl, and Python.

A reference of RESTful Management resources is found in [RESTful Management API Resources](#). Only a few example resources and JSON payloads will be mentioned in this guide.

The RESTful Management API is active once the PowerMedia XMS is installed and running.

3. Firefox RESTClient Utility

While the RESTful Management API is intended to be used as part of an overall management system written by the customer, there is convenient way to exercise the API and become familiar with its operation. The Firefox web browser (<http://www.mozilla.org>) supplies a free extension, RESTClient, which allows RESTful methods to be generated and sent to a RESTful service. It is similar to the XMSTool used with the call and media control RESTful API.

Accessing RESTClient

Proceed as follows to access RESTClient:

1. From an up-to-date Firefox browser, use the main Firefox pull-down menu and select **Add-ons**.
2. Enter **restclient** in the search box at the upper right corner of the page.
An entry for **RESTClient, a debugger for RESTful web services** will be observed under **Available Add-ons**.
3. Click on **Install**.
4. Restart Firefox when the installation is complete. The RESTClient will appear under the Extensions tab in Add-ons.

4. Configuring and Using the RESTClient Utility

Before the RESTClient is started, a security exception must be put in place for the HTTPS connection that will be used to PowerMedia XMS. Use a regular Firefox browser window, (not the RESTClient) and go to **https://<xms_ip_address>:10443**.

A security exception will be generated by the non-verified security certificate supplied with PowerMedia XMS for the RESTful Management API. Handle the exception with: Understand the Risks/Add Exception/Confirm Security Exception. Allow the exception will remain permanently stored. For more information, refer to the CentOS HTTPS Setup for Console Use section in the *Dialogic® PowerMedia™ XMS Quick Start Guide* or *Dialogic® PowerMedia™ XMS Installation and Configuration Guide*.

Proceed as follows to start RESTClient:

1. From the main Firefox pull-down menu, select **Web Developer**.
2. Click on **RESTClient**.
3. Select **Headers** and **Custom Header**.
4. Enter:
Name: Content-Type, Value: application/json
Name: Accept, Value: application/json

Note: Two Request Headers must be entered.

Basic Authentication should also be activated. Under Authentication/Basic Authentication, set:

1. Enter User Name: **admin**
Enter Password: **admin**
Remember Me – checked off
2. Select **OK**.

The remainder of this section gives examples for each supported HTTP method. However, refer to [RESTful Management API Resources](#) for details on using the resource and method.

Using GET with the RESTClient

1. Select **GET** from the Method pull-down menu.
2. Enter the HTTPS URL for the resource desired.
The format used here is **https://<xms_ip_address>:10443/resource**.
For example, to look at the domain name server setting (DNS) for the XMS system at 172.31.0.2, the URL would be **https://172.31.0.2:10443/network/dns**.
3. View the Response Header and Response Body by clicking their respective tabs.

The following example shows the JSON representation of the DNS requested above:

```
{
  "hostname" : "novalocal",
  "search" : "novalocal",
  "nameserver" : [
    {
      "addr" : "172.31.0.3"
    }
  ]
}
```

Using PUT with the RESTClient

1. Select **PUT** from the Method pull-down.
2. Enter the HTTPS URL for the resource desired.
The format is **https://<xms_ip_address>:10443/resource**.
For example, to set the SIP call routing to be used, the URL would be **https://172.31.0.2:10443/routing**.

The JSON describing the desired routes would be entered in the Request Body field.

The following example shows how to set all routes to their original values:

```
{
  "routes" : [
    {
      "pattern" : "^sip:annc.*",
      "application" : "NETANN"
    },
    {
      "pattern" : "^sip:conf=.*",
      "application" : "NETANN"
    },
    {
      "pattern" : "^sip:dialog.*",
      "application" : "VXML"
    },
    {
      "pattern" : "^sip:.*",
      "application" : "app"
    }
  ]
}
```

Requests can be entered into the Body text field, copied and pasted into the field or read out of a file.

Using POST with the RESTClient

1. Select **POST** from the Method pull-down menu.
2. Enter the HTTPS URL for the resource desired.
The format is **https://<xms_ip_address>:10443/resource**.
For example, to create a system backup, the URL would be **https://172.31.0.2:10443/system/backup**.

The following example shows what would be returned in the Response Body:

```
{
  "system_backup" : [
    {
      "resources" : [
        {
          "id" : "xmsbackup-20121011-161653.tar.gz",
          "uri" : "\/system\/backup\/xmsbackup-20121011-161653.tar.gz"
        }
      ]
    }
  ]
}
```

In addition, the backup file `/etc/xms/backup/xmsbackup-20121011-161653.tar.gz` would be created.

Using DELETE with the RESTClient

1. Select **DELETE** from the Method pull-down menu.
2. Enter the HTTPS URL for the resource desired.
The format is **https://<xms_ip_address>:10443/resource**.
For example, to delete the media file `/var/lib/xms/media/en-US/vxml/recorded/record-120921-085752-0000.wav`, the URL would be **https://172.31.0.2:10443/media/vxml/recorded/record-120921-085752-0000.wav**.

Note: The root media directory is `/var/lib/xms/media/en-US/` and does not need to be specified.

5. RESTful Management API Resources

The RESTful Management API supports JSON data format. The format is specified using standard mime-types. The client should use the Accept header to specify the format that it wishes to receive. The Content-Type header specifies the mime-type of the request's or response's content.

The RESTful Management API can be accessed in two ways:

- Locally over HTTP
Use the base URL `http://127.0.0.1:10080/`
- Externally over HTTPS
The https interface is provided by the `lighttpd` service acting as proxy.
Use `https://<ipaddress>:10443/`
The https service uses http basic authentication and defines a single user "admin" with the password "admin".

Clicking on the resource or sub-resource will:

- Provide its definition
- Provide valid values for the parameters that can be set
- Define how each valid method affects the resource
- Give an example of a request and a response payload

Resource	Sub-Resource	HTTP Methods Supported
/system		GET, PUT
	/info	GET
	/time	GET, PUT
	/backup	GET, POST, DELETE
	/restore	GET, PUT
	/upgrade	GET, PUT, POST, DELETE
	/nfsmount	GET, PUT

Resource	Sub-Resource	HTTP Methods Supported
/sip		GET, PUT
/rtp		GET, PUT
/trust		GET, PUT
/httpclient		GET, PUT
/services		GET, PUT
/logs		GET
	/process	GET, PUT, DELETE
	/mediasubsystem	GET, PUT, DELETE
/license		GET, PUT, POST, DELETE
/codecs		GET, PUT
/routing		GET, PUT
/msml		GET, PUT
/media		GET, POST, DELETE
/tones		GET, PUT

Resource	Sub-Resource	HTTP Methods Supported
/network		GET
	/interface	GET, PUT
	/dns	GET, PUT
/mrcpclient		GET, PUT
	/global	GET, PUT
	/speechserver_sample	GET, PUT
	/speechserver_speechserver1	GET, PUT
/netann		GET
	/global	GET, PUT
	/conference	GET, PUT
/resource		GET
	/active	GET
	/groups	GET
	/licenses	GET

Resource	Sub-Resource	HTTP Methods Supported
/snmp		GET
	/trap-destinations	GET, PUT
	/v2c-communities	GET, PUT
	/v3-users	GET, PUT
	/thresholds	GET, PUT
/vxml		GET
	/vxmlinterpreter	GET, PUT
/xmsrest		GET
	/general	GET, PUT
	/trusted	GET, PUT
/msrp		GET
	/global	GET, PUT

6. List of Available Resources

/system

Resource URI

/system

Resources

Resource	Description
info	Gets system information resource
network	Gets network configuration resource
time	Gets time and date configuration resource

HTTP GET

Retrieves all available system resources.

GET /system

Method	Response Payload
JSON	<pre>{ "state" : "running", "version" : "1.0", "resources" : [{ "uri" : "\/system\/info" }, { "uri" : "\/system\/network" }, { "uri" : "\/system\/time" }] }</pre>

HTTP PUT

Restarts or shutdowns the server.

PUT /system

Valid "state" settings:

- shutdown
- restart
- running (readonly)

Method	Request Payload	Response Payload
JSON	<pre>{ "state" : "shutdown" }</pre>	<pre>{ "state" : "shutdown", "resources" : [{ "uri" : "\/system\/info" }, { "uri" : "\/system\/network" }, { "uri" : "\/system\/time" }] }</pre>

/system/info

Resource URI

/system/info

HTTP GET

Retrieves information for a single resource.

GET /system/info

Method	Response Payload
JSON	<pre>{ "os_release" : "Fedora release 14 (Laughlin) ", "os_version" : "Linux version 2.6.35.14-96.fc14.i686.PAE (mockbuild@x86-01.phx2.fedoraproject.org) (gcc version 4.5.1 20100924 (Red Hat 4.5.1-4) (GCC)) #1 SMP Thu Sep 1 12:31:46 UTC 2011 ", "uptime" : 3017268, "load_avg" : [{ "1" : 0.13, "5" : 0.1, "15" : 0.14 }], "memory" : [{ "total" : 4123224, "used" : 3206668 }], "disk" : [{ "total" : 145947208, "used" : 98588080 }] }</pre>

/system/time

Resource URI

/system/time

HTTP GET

Retrieves information for system time.

GET /system/time

Method	Response Payload
JSON	<pre>{ "system_time": { "time": "Fri Oct 26 19:15:39 2012", "zone": "America/New York", "zone_offset" : -18000, "utc": "no", "syncntp": "yes", "ntpserver": [{ "addr": "0.centos.pool.ntp.org", "iburst": "false", "maxpoll": "10", "minpoll": "6" }, { "addr": "1.centos.pool.ntp.org", "iburst": "false", "maxpoll": "10", "minpoll": "6" }, { "addr": "2.centos.pool.ntp.org", "iburst": "false", "maxpoll": "10", "minpoll": "6" }] } }</pre>

HTTP PUT

Modifies system time.

PUT /system/time

Method	Request Payload	Response Payload
JSON	<pre>{ "system_time": { "zone": "America/xyz", "utc": "yes", "syncntp": "yes", } }</pre>	<pre>{ "system_time": { "time": "Fri Oct 26 19:15:39 2012", "zone": "America/xyz", "zone_offset" : -17000, "utc": "yes", "syncntp": "yes", "ntpserver": [{ "addr": "0.centos.pool.ntp.org", "iburst": "false", "maxpoll": "10", "minpoll": "6" }, { "addr": "1.centos.pool.ntp.org", "iburst": "false", "maxpoll": "10", "minpoll": "6" }] } }</pre>

Method	Request Payload	Response Payload
		<pre> }, { "addr": "2.centos.pool.ntp.org", "iburst": "false", "maxpoll": "10", "minpoll": "6" }] } } </pre>

/system/backup

Resource URI

/system/backup

HTTP GET

Retrieves all available backup files.

GET /system/backup

Method	Response Payload
JSON	<pre> { "system_backup": { "resources": [{ "id": "xmsbackup-20120619-160125.tar.gz", "uri": "/system/backup/xmsbackup-20120619-160125.tar.gz" }, { "id": "xmsbackup-20120620-120928.tar.gz", "uri": "/system/backup/xmsbackup-20120620-120928.tar.gz" }, { "id": "xmsbackup-20120620-120935.tar.gz", "uri": "/system/backup/xmsbackup-20120620-120935.tar.gz" }] } } </pre>

Single Instance

Resource URI

/system/backup/xmsbackup-20120619-160125.tar.gz

Download a single backup file.

GET /system/backup/xmsbackup-20120619-160125.tar.gz

Response

A binary data of the backup file.

HTTP POST

Creates a system backup file.

POST /system/backup

Method	Response Payload
JSON	<pre>{ "system_backup": { "resources": [{ "id": "xmsbackup-20120619-160125.tar.gz", "uri": "/system/backup/xmsbackup-20120619-160125.tar.gz" }, { "id": "xmsbackup-20120620-120928.tar.gz", "uri": "/system/backup/xmsbackup-20120620-120928.tar.gz" }, { "id": "xmsbackup-20120620-120935.tar.gz", "uri": "/system/backup/xmsbackup-20120620-120935.tar.gz" }] } }</pre>

Uploads a system backup file.

Payload content-type="application/x-gzip"

POST /system/backup/mybackup.tar.gz

Method	Response Payload
JSON	<pre>{ "system backup": { "resources": [{ "id": "xmsbackup-20120619-160125.tar.gz", "uri": "/system/backup/xmsbackup-20120619-160125.tar.gz" }, { "id": "xmsbackup-20120620-120928.tar.gz", "uri": "/system/backup/xmsbackup-20120620-120928.tar.gz" }, { "id": "mybackup.tar.gz", "uri": "/system/backup/xmsbackup-20120620-120935.tar.gz" }] } }</pre>

HTTP DELETE

Deletes a system backup file.

DELETE /system/backup/mybackup.tar.gz

/system/restore

Resource URI

/system/restore

HTTP GET

Retrieves all available backup files for restore.

GET /system/restore

Method	Response Payload
JSON	<pre>{ "system_restore": { "resources": [{ "id": "xmsbackup-20120619-160125.tar.gz", "uri": "/system/restore/xmsbackup-20120619-160125.tar.gz" }, { "id": "xmsbackup-20120620-120928.tar.gz", "uri": "/system/restore/xmsbackup-20120620-120928.tar.gz" }, { "id": "xmsbackup-20120620-120935.tar.gz", "uri": "/system/restore/xmsbackup-20120620-120935.tar.gz" }] } }</pre>

HTTP PUT

Restores system from a system backup file.

```
PUT /system/restore/xmsbackup-20120619-160125.tar.gz
```

/system/upgrade

Resource URI

```
/system/upgrade
```

HTTP GET

Retrieves all available upgrade files.

```
GET /system/upgrade
```

Method	Response Payload
JSON	<pre>{ "system_upgrade": { "resources": [{ "id": "dialogic_xms_trunk.3375.tgz", "uri": "/system/upgrade/dialogic_xms_trunk.3375.tgz" }] } }</pre>

HTTP PUT

Upgrades system from a system upgrade file.

```
PUT /system/upgrade/xmsbackup-20120619-160125.tar.gz
```

HTTP POST

Upload a system backup file.

Payload content-type="application/x-gzip"

```
POST /system/upgrade/dialogic_xms_trunk.3375.tgz
```

Method	Response Payload
JSON	<pre>{ "system_upgrade": { "resources": [{ "id": "dialogic_xms_trunk.3375.tgz", "uri": "/system/upgrade/dialogic_xms_trunk.3375.tgz" }] } }</pre>

HTTP DELETE

Deletes a system upgrade file.

```
DELETE /system/upgrade/dialogic_xms_trunk.3375.tgz
```

/system/nfsmount

Resource URI

```
/system/nfsmount
```

HTTP GET

Retrieves all NFS mount points.

```
GET /system/nfsmount
```

Method	Response Payload
JSON	<pre>{ "nfsmounts": [{ "device": "onyx2:/files/Builds/G4PP/", "mount point": "/mnt/jane", "options": "defaults", "status": "disable" }, { "device": "onyx:/files/Builds/G2MS/", "mount point": "/mnt/lingx2", "options": "defaults", "status": "disable" }] }</pre>

HTTP PUT

Adds, deletes, or modifies NFS mount points.

```
PUT /system/nfsmount
```

Method	Request Payload	Response Payload
JSON	<pre>{ "nfsmounts": [{ "device": "onyx2:/files/Builds/G4PP/", "mount_point": "/mnt/jane2", "options": "ro", }, { "device": "onyx:/files/Builds/G2MS/", "mount_point": "/mnt/lingx2", "options": "defaults", }, { "device": "onyx:/files/Builds/new/", "mount_point": "/mnt/onyx/new", "options": "defaults", }] }</pre>	<pre>{ "nfsmounts": [{ "device": "onyx2:/files/Builds/G4PP/", "mount_point": "/mnt/jane2", "options": "defaults", "status": "enable" }, { "device": "onyx:/files/Builds/G2MS/", "mount point": "/mnt/lingx2", "options": "defaults", "status": "disable" }, { "device": "onyx2:/files/Builds/new/", "mount point": "/mnt/onyx/new", "options": "defaults", "status": "enable" }] }</pre>

/sip

Resource URI

/sip

HTTP GET

Retrieves the SIP interface settings.

GET /sip

Method	Response Payload
JSON	<pre>{ "Board_1" : { "app_srv_access" : "no", "sip_ipaddr" : "DEFAULT", "sip_port" : "5060", "transport" : "UDP" } }</pre>

HTTP PUT

Modifies the SIP interface IP address, port number and transport. Enables an access control list that defines the hosts allowed to connect to the SIP interface.

PUT /sip

Valid "transport" settings:

- UDP
- UDP_TCP

Method	Request Payload	Response Payload
JSON	<pre>{ "Board_1" : { "app_srv_access" : "no", "sip_ipaddr" : "DEFAULT", "sip_port" : "5060", "transport" : "UDP" } }</pre>	<pre>{ "Board_1" : { "app_srv_access" : "no", "sip_ipaddr" : "DEFAULT", "sip_port" : "5060", "transport" : "UDP" } }</pre>

/rtp

Resource URI

/rtp

HTTP GET

Retrieves a network interface name that is used by media engine RTP and a list of available interface names and IP addresses.

GET /rtp

Method	Response Payload
JSON	<pre>{ "ifname":"enp0s3", "if_ipv4addr":"", "if_ipv6addr":"", "tos":"0", "rtp_timeout_audio":"30000", "rtcp_timeout_audio":"15000", "rtp_timeout_video":"30000", "rtcp_timeout_video":"15000", "ifitems":[["enp0s3","",""], ["enp0s8","","fda8:6c3:ce53:a890::2"]], "lifetime":"2147483648", "key rotation count":"1", "accept_srtp":"yes", "enforce_srtp":"no", "unencrypted_rtp":"no", "unencrypted_rtcp":"no", "window_size_hint":"64", "mrt":[] }</pre>

HTTP PUT

PUT /rtp

Method	Request Payload	Response Payload
JSON	<pre>{ "ifname": "enp03" }</pre>	<pre>{ "ifname": "enp0s3", "if_ipv4addr": "", "if_ipv6addr": "", "tos": "0", "rtp_timeout_audio": "30000", "rtcp_timeout_audio": "15000", "rtp_timeout_video": "30000", "rtcp_timeout_video": "15000", "ifitems": [["enp0s3", "", ""], ["enp0s8", "", "fda8:6c3:ce53:a890::2"]], "lifetime": "2147483648", "key_rotation_count": "1", "accept_srtp": "yes", "enforce_srtp": "no", "unencrypted_rtp": "no", "unencrypted_rtcp": "no", "window_size_hint": "64", "mrt": [] }</pre>

/trust

Resource URI

/trust

HTTP GET

Sets and retrieves the trusted hosts that can communicate via the SIP port.

GET /trust

Method	Response Payload
JSON	<pre>{ "trusted_addresses" : ["192.168.195.12", "192.168.195.204"] }</pre>

HTTP PUT

Modifies the trusted hosts configuration.

PUT /trust

Method	Request Payload	Response Payload
JSON	<pre>{ "trusted_addresses" : ["192.168.195.12", "192.168.195.204"] }</pre>	<pre>{ "trusted_addresses" : ["192.168.195.12", "192.168.195.204"] }</pre>

/httpclient

Resource URI

/httpclient

HTTP GET

Retrieves the HTTP client configuration.

GET /httpclient

Method	Response Payload
JSON	<pre>{ "cache": "no", "max_stale": "33", "max_age": "500" }</pre>

HTTP PUT

Configures the HTTP client resource.

PUT /httpclient

Method	Request Payload	Response Payload
JSON	<pre>{ "cache": "yes", "max_stale": "0", "max_age": "30" }</pre>	<pre>{ "cache": "yes", "max_stale": "0", "max_age": "30" }</pre>

/services

Resource URI

/services

HTTP GET

Retrieves all available system services and the overall run state of the system services.

Valid "state" values:

- STOPPED
- STARTING
- RUNNING
- STOPPING
- FAILED

GET /services

Method	Response Payload
JSON	<pre> { "status":200, "reason":"ok", "overallStatus":"RUNNING", "graceful_shutdown_timeout":120, "graceful_shutdown_timer":0, "services":[{ "id":"hmp", "state":"RUNNING", "description":"Media Processing Service", "optional":"no", "onStart":"yes" }, { "id":"perfmanager", "state":"RUNNING", "description":"Performance Manager", "optional":"yes", "onStart":"yes" }, { "id":"eventmanager", "state":"RUNNING", "description":"Event Manager", "optional":"yes", "onStart":"yes"}, { "id":"broker", "state":"RUNNING", "description":"Message Routing Service", "optional":"no", "onStart":"yes" }, { "id":"xmserver", "state":"RUNNING", "description":"Signaling and Media Service", "optional":"no", "onStart":"yes" }, { "id":"httpclient", "state":"RUNNING", "description":"HTTP Client", "optional":"yes", "onStart":"yes" }, { "id":"mrcpclient", "state":"RUNNING", "description":"MRCP Client", "optional":"yes", "onStart":"yes" }, { "id":"rtcweb", "state":"RUNNING", "description":"RTCWeb Signaling Service", "optional":"yes", "onStart":"yes" }, { "id":"appmanager", "state":"RUNNING", "description":"Application Interface Service", "optional":"no", </pre>

Method	Response Payload
	<pre> "onStart":"yes" }, { "id":"xmsrest", "state":"RUNNING", "description":"RESTful Call/Media Control Service", "optional":"yes", "onStart":"yes" }, { "id":"netann", "state":"RUNNING", "description":"NETANN Service", "optional":"yes", "onStart":"yes" }, { "id":"vxml", "state":"RUNNING", "description":"VXML Service", "optional":"yes", "onStart":"yes" }, { "id":"msml", "state":"RUNNING", "description":"MSML Service", "optional":"yes", "onStart":"yes" }, { "id":"msrpservice", "state":"RUNNING", "description":"MSRP Service", "optional":"yes", "onStart":"yes" }, { "id":"faxservice", "state":"STOPPED", "description":"Fax Service", "optional":"yes", "onStart":"no" }, { "id":"verification", "state":"RUNNING", "description":"System/Application Verification Service", "optional":"yes", "onStart":"yes" }, { "id":"xmssysstats", "state":"RUNNING", "description":"System Statistics Collector Service", "optional":"yes", "onStart":"yes" }, { "id":"cdrserver", "state":"RUNNING", "description":"CDR Service", "optional":"yes", "onStart":"yes" }, { "id":"wsapiserver", </pre>

Method	Response Payload
	<pre> "state":"STOPPED", "description":"WS Api Server", "optional":"yes", "onStart":"no" }] }</pre>

Single Instance

Resource URI

```

/services/appmanager
/services/broker
/services/xmsserver
/services/restapi
/services/msmlserver
/services/mediasubsystem
```

Retrieves information for a single service resource.

```
GET /services/broker
```

Method	Response Payload
JSON	<pre> { "service" : { "id" : "appmanager", "state" : "RUNNING", "description" : "The appmanager process" } }</pre>

HTTP PUT

Modifies the system services overall run state.

Valid "state" settings:

- RUNNING
- STOPPED

Note: The "restart_required" parameter is read-only and is an indication that any change requires a services restart.

```
PUT /services
```

Method	Request Payload	Response Payload
JSON	<pre>{ "state" : "STOPPED" }</pre>	<pre>{ "state":"STOPPING", "restart_required":"no", "services" : [{ "id" : "appmanager", "uri" : "\services\appmanager" }, { "id" : "broker", "uri" : "\services\broker" }, { "id" : "xmserver", "uri" : "\services\xmserver" }, { "id" : "restapi", "uri" : "\services\restapi" }, { "id" : "mediasubsystem", "uri" : "\services\mediasubsystem" },] }</pre>

/logs

Resource URI

/logs

HTTP GET

Retrieves all available log types.

GET /logs

Method	Response Payload
JSON	<pre>{ "logs" : [{ "id" : "mediasubsystem", "uri" : "\logs\mediasubsystem" }, { "id" : "process", "uri" : "\logs\process" }] }</pre>

/logs/process

Resource URI

/logs/process

HTTP GET

Retrieves all available process log types.

GET /logs/process

The attribute keep_days may be a number 0..n or the string "forever".

Method	Response Payload
JSON	<pre>{ "logs" : { "options" : { "level" : "production", "keep_days" : "forever" }, "resources" : [{ "id" : "appmanager", "uri" : "\/logs\/process\/appmanager" }, { "id" : "broker", "uri" : "\/logs\/process\/broker" }, { "id" : "xmserver", "uri" : "\/logs\/process\/xmserver" }, { "id" : "xmsrest", "uri" : "\/logs\/process\/xmsrest" }] } }</pre>

Single Instance

Resource URI

```
/logs/process/appmanager  
/logs/process/broker  
/logs/process/xmsserver  
/logs/process/xmsrest
```

Retrieves information for a single log resource.

```
GET /logs/process/appmanager?start=20111101-090000&stop=20111103-235959
```

Method	Response Payload
JSON	<pre>{ "log_resource" : { "resource" : { "id" : "appmanager" }, "files" : [{ "uri" : "\\logs\\process\\appmanager\\appmanager-20111101- 132511.log" }, { "uri" : "\\logs\\process\\appmanager\\appmanager-20111102- 091157.log" }, { "uri" : "\\logs\\process\\appmanager\\appmanager-20111102- 134431.log" }, { "uri" : "\\logs\\process\\appmanager\\appmanager-20111103- 145245.log" }] } }</pre>

HTTP PUT

Modifies the system logging operation.

```
PUT /logs/process
```

Method	Request Payload	Response Payload
JSON	<pre>{ "logs" : { "options" : { "level" : "debug", "keep_days" : "7" } } }</pre>	<pre>{ "logs" : { "options" : { "level" : "debug", "keep_days" : "7" }, "resources" : [{ "id" : "appmanager", "uri" : "\logs\process\appmanager" }, { "id" : "broker", "uri" : "\logs\process\broker" }, { "id" : "xmserver", "uri" : "\logs\process\xmserver" }, { "id" : "xmsrest", "uri" : "\logs\process\xmsrest" }] } }</pre>

HTTP DELETE

Deletes logs for a single process.

```
DELETE /logs/process/appmanager?start=20111101-090000&stop=20111103-235959
```

If no start and stop parameters are defined then all of the logging is deleted for this process.

Deletes all process logs.

```
DELETE /logs/process?start=20111101-090000&stop=20111103-235959
```

If no start and stop parameters are defined then all of the logging is deleted for all processes.

/logs/mediasubsystem

Resource URI

```
/logs/mediasubsystem
```

HTTP GET

Retrieves all available mediasubsystem log types.

```
GET /logs/mediasubsystem
```

Method	Response Payload
JSON	<pre>{ "logs" : { "options" : { "keep days" : "7" }, "resources" : [{ "id" : "board", "uri" : "\logs\mediasubsystem\board" }, { "id" : "cliagent", "uri" : "\logs\mediasubsystem\cliagent" }, { "id" : "clusterpkg", "uri" : "\logs\mediasubsystem\clusterpkg" }, { "id" : "confslot", "uri" : "\logs\mediasubsystem\confslot" }, { "id" : "drv", "uri" : "\logs\mediasubsystem\drv" }, { "id" : "rtflog", "uri" : "\logs\mediasubsystem\rtflog" }, { "id" : "snmp", "uri" : "\logs\mediasubsystem\snmp" }] } }</pre>

Single Instance

Resource URI

```
/logs/mediasubsystem/board
/logs/mediasubsystem/cliagent
/logs/mediasubsystem/clusterpkg
/logs/mediasubsystem/confslot
/logs/mediasubsystem/drv
/logs/mediasubsystem/rtflog
/logs/mediasubsystem/snmp
```

Retrieves information for a single log resource. If no start and stop parameters are specified then all of the available logs for that resource are returned.

```
GET /logs/mediasubsystem/rtflog?start=20111101-090000&stop=20111103-235959
```

Method	Response Payload
JSON	<pre>{ "log_resource" : { "resource" : { "id" : "rtflog" }, "files" : [{ "uri" : "\\logs\\mediasubsystem\\rtf\\rtflog-LOCAL-20111101-05h03m46.833s.txt" }, { "uri" : "\\logs\\mediasubsystem\\rtf\\rtflog-LOCAL-20111102-04h45m47.829s.txt" }] } }</pre>

HTTP PUT

Modifies the mediasubsystem logging operation.

PUT /logs/mediasubsystem

Method	Request Payload	Response Payload
JSON	<pre>{ "logs" : { "options" : { "keep_days" : "3" } } }</pre>	<pre>{ "logs" : { "options" : { "keep_days" : "3" }, "resources" : [{ "id" : "board", "uri" : "\\logs\\mediasubsystem\\board" }, { "id" : "cliagent", "uri" : "\\logs\\mediasubsystem\\cliagent" }, { "id" : "clusterpkg", "uri" : "\\logs\\mediasubsystem\\clusterpkg" }, { "id" : "confslot", "uri" : "\\logs\\mediasubsystem\\confslot" }, { "id" : "drv", "uri" : "\\logs\\mediasubsystem\\drv" }, { "id" : "rtflog", "uri" : "\\logs\\mediasubsystem\\rtflog" }, { "id" : "snmp", "uri" : </pre>

Method	Request Payload	Response Payload
		<pre>"\logs\mediasubsystem\snmp" }] } }</pre>

HTTP DELETE

Deletes a single type of multimedia system logs.

```
DELETE /logs/mediasubsystem/rtflog?start=20111101-090000&stop=20111103-235959
```

If no start and stop parameters are defined then all of the logging is deleted for this resource.

Deletes all multimedia system logs.

```
DELETE /logs/mediasubsystem?start=20111101-090000&stop=20111103-235959
```

If no start and stop parameters are defined then all of the multimedia subsystem logging is deleted.

/license

Resource URI

```
/license
```

HTTP GET

Retrieves system license information.

```
GET /license
```

Method	Response Payload
JSON	<pre>{ "licenses" : { "resources" : [{ "id" : "default.lic", "uri" : uri="\license/default.lic" }, { "id" : "temp.lic" , "uri" : uri="\license/temp.lic" }, { "id" : "verification.lic", "uri" : uri="\license/verification.lic" }], "features" : [{ "name" : "Advanced Video", "value" : 2 }, { "name" : "Basic Audio", "value" : 2 }, { "name" : "GSMAMR Audio", "value" : 2 }] } }</pre>

Method	Response Payload
	<pre> }, { "name" : "HD Voice", "value" : 2 }, { "name" : "High Resolution Video", "value" : 2 }, { "name" : "LBR Audio", "value" : 2 }, { "name" : "MRB", "value" : 0 }, { "name" : "MRCP Speech Server", "value" : 2 }, { "name" : "MSRP", "value" : 0 }] } } </pre>

Single Instance

Retrieves information for a single license resource.

```
GET /license/production.lic
```

Method	Response Payload
JSON	<pre>{ "license" : { "id" : "verification.lic", "type" : "Verification", "expires" : "permanent", "status" : "active", "features" : [{ "name" : "Advanced Video", "value" : 2 }, { "name" : "Basic Audio", "value" : 2 }, { "name" : "GSMAMR Audio", "value" : 2 }, { "name" : "HD Voice", "value" : 2 }, { "name" : "High Resolution Video", "value" : 2 }, { "name" : "LBR Audio", "value" : 2 }, { "name" : "MRB", "value" : 0 }, { "name" : "MRCP Speech Server", "value" : 2 }, { "name" : "MSRP", "value" : 0 }] } }</pre>

HTTP PUT

Modifies an individual license status.

Valid "status" values:

- active
- inactive

```
PUT /license/production.lic
```

Method	Request Payload	Response Payload
JSON	<pre>{ "status" : "active" }</pre>	<pre>{ "license" : { "id" : "verification.lic", "type" : "Verification", "expires" : "permanent", "status" : "active", "features" : [{ "name" : "Advanced Video", "value" : 2 }, { "name" : "Basic Audio", "value" : 2 }, { "name" : "GSMAMR Audio", "value" : 2 }, { "name" : "HD Voice", "value" : 2 }, { "name" : "High Resolution Video", "value" : 2 }, { "name" : "LBR Audio", "value" : 2 }, { "name" : "MRB", "value" : 0 }, { "name" : "MRCP Speech Server", "value" : 2 }, { "name" : "MSRP", "value" : 0 }] } }</pre>

HTTP POST

Uploads a new license. On completion, the license will be in an inactive state. Use PUT to activate.

```
POST /license/<production-new.lic>
```

Method	Request Payload	Response Payload
JSON	The request payload is the raw license file data. The mime type must be text/plain. <pre>Content-Type: text/plain</pre>	<pre>{ "license" : { "id" : "verification-new.lic", "type" : "Verification", "expires" : "permanent", "status" : "inactive", "features" : [{ "name" : "Advanced Video", "value" : 2 }, { "name" : "Basic Audio", "value" : 2 }, { "name" : "GSMAMR Audio", "value" : 2 }, { "name" : "HD Voice", "value" : 2 }, { "name" : "High Resolution Video", "value" : 2 }, { "name" : "LBR Audio", "value" : 2 }, { "name" : "MRB", "value" : 0 }, { "name" : "MRCP Speech Server", "value" : 2 }, { "name" : "MSRP", "value" : 0 }] } }</pre>

HTTP DELETE

Deletes a license. License must be inactive.

```
DELETE /license/production.lic
```

/codecs

Resource URI

```
/codecs
```

HTTP GET

Retrieves the audio and video codec settings. The codecs are returned in priority order.

```
GET /codecs
```

Method	Response Payload
JSON	<pre> { "audio_codecs" : [{ "amr-wb" : { "enabled" : "yes" } }, { "g723" : { "enabled" : "yes" } }, { "amr-nb" : { "enabled" : "yes" } }, { "g729" : { "enabled" : "yes" } }, { "pcmu" : { "enabled" : "yes" } }, { "pcma" : { "enabled" : "yes" } }, { "g722" : { "enabled" : "yes" } }, { "g726" : { "enabled" : "yes" } }], "video_codecs" : [{ "h264" : { "enabled" : "yes", "bitrate" : "768000", "fps" : "25", "level" : "22", "profile" : "66", "sample_rate" : "0", "size" : "vga" } }, { "h263" : { "enabled" : "yes", "bitrate" : "384000", "fps" : "30", "level" : "30", "profile" : "0", "sample_rate" : "0", "size" : "cif" } }] } </pre>

HTTP PUT

Modifies the supported codec configuration.

PUT /codecs

The following tables provide the valid settings for PowerMedia XMS system.

codec	level	size	fps	bps
h264	3.1	vga	30	2000000
h264	3.1	vga	30	768000
h264	3	vga	25	768000
h264	2.2	vga	25	768000
h264	2.1	cif	30	384000
h264	2	cif	30	384000
h264	1.3	cif	30	384000
h264	1.2	cif	15	384000
h264	1.1	qcif	30	192000
h264	1b	qcif	15	128000
h264	1	qcif	15	42000

codec	level	size	fps	bps
mp4v-es	3	cif	30	384000
mp4v-es	2	cif	15	128000
mp4v-es	1	qcif	15	64000
mp4v-es	0	qcif	15	42000

codec	level	size	fps	bps
h263	30	cif	30	384000
h263	30	cif	15	384000
h263	30	cif	10	384000

codec	level	size	fps	bps
h263	30	qcif	30	384000
h263	30	qcif	15	384000
h263	20	cif	30	128000
h263	20	cif	15	128000
h263	20	cif	10	128000
h263	20	qcif	30	128000
h263	20	qcif	15	128000

codec	level	size	fps	bps
h263-1998	30	cif	30	384000
h263-1998	30	cif	15	384000
h263-1998	30	cif	10	384000
h263-1998	30	qcif	30	384000
h263-1998	30	qcif	15	384000
h263-1998	20	cif	30	128000
h263-1998	20	cif	15	128000
h263-1998	20	cif	10	128000
h263-1998	20	qcif	30	128000
h263-1998	20	qcif	15	128000

Method	Request Payload	Response Payload
JSON	<pre>{ "audio codecs" : [{ "amr-wb" : { "enabled" : "yes" } }, { "g723" : { "enabled" : "yes" } }] }</pre>	<pre>{ "audio codecs" : [{ "amr-wb" : { "enabled" : "yes" } }, { "g723" : { "enabled" : "yes" } }] }</pre>

Method	Request Payload	Response Payload
	<pre> }, { "amr-nb" : { "enabled" : "yes" } }, { "g729" : { "enabled" : "yes" } }, { "pcmu" : { "enabled" : "yes" } }, { "pcma" : { "enabled" : "yes" } }, { "g722" : { "enabled" : "yes" } }, { "g726" : { "enabled" : "yes" } }], "video_codecs" : [{ "h264" : { "enabled" : "yes", "bitrate" : "768000", "fps" : "25", "level" : "22", "profile" : "66", "sample_rate" : "0", "size" : "vga" } }, { "h263" : { "enabled" : "yes", "bitrate" : "384000", "fps" : "30", "level" : "30", "profile" : "0", "sample_rate" : "0", "size" : "cif" } }] } </pre>	<pre> }, { "amr-nb" : { "enabled" : "yes" } }, { "g729" : { "enabled" : "yes" } }, { "pcmu" : { "enabled" : "yes" } }, { "pcma" : { "enabled" : "yes" } }, { "g722" : { "enabled" : "yes" } }, { "g726" : { "enabled" : "yes" } }], "video_codecs" : [{ "h264" : { "enabled" : "yes", "bitrate" : "768000", "fps" : "25", "level" : "22", "profile" : "66", "sample_rate" : "0", "size" : "vga" } }, { "h263" : { "enabled" : "yes", "bitrate" : "384000", "fps" : "30", "level" : "30", "profile" : "0", "sample_rate" : "0", "size" : "cif" } }] } </pre>

/routing

Routing rules map inbound SIP URIs to their applications. Each rule consists of a pattern and an application name.

Resource URI

/routing

HTTP GET

Sets and retrieves the routing configuration.

GET /routing

Method	Response Payload
JSON	<pre>{ "routes" : [{ "pattern" : "^sip:100.*", "application" : "app" }, { "pattern" : "^sip:101.*", "application" : "app" }] }</pre>

HTTP PUT

Modifies the routing configuration.

PUT /routing

Method	Request Payload	Response Payload
JSON	<pre>{ "routes" : [{ "pattern" : "^sip:100.*", "application" : "app" }, { "pattern" : "^sip:101.*", "application" : "app" }, { "pattern" : "^sip:102.*", "application" : "app2" }] }</pre>	<pre>{ "routes" : [{ "pattern" : "^sip:100.*", "application" : "app" }, { "pattern" : "^sip:101.*", "application" : "app" }, { "pattern" : "^sip:102.*", "application" : "app2" }] }</pre>

/msml

Resource URI

/msml

HTTP GET

Sets and retrieves all MSML server settings.

GET /msml

Method	Response Payload
JSON	<pre>{ "version": "1.1", "http_caching": "no", "schema_validation": "no", "adaptor_port": "32868", "storage_directory": "/var/lib/xms/media/en US", "content_type": "xml", "encoding": "utf_8", "clear_db": "yes", "dtmf_start_time": "no", "adv_digit_pattern": "no", "video_fast_update": "INFO", "video_bandwidth": "512", "conf_agc_default": "no", "default_amr_alignment": "BANDWIDTH_EFFICIENT", "dtmf_detect_mode": "RFC2833", "dns_cache_timeout": "60", "cert_verify_peer": "no", "cert_verify_host": "no", "cpa": [{ "config1": { "cnosig": 40000, "no_answer": 30000, "pamd_failtime": 4000 } }] }</pre>

HTTP PUT

Modifies the MSML server configuration.

PUT /msml

Valid "version" settings:

- 1.0
- 1.1

Valid "content_type" settings:

- xml
- msml_xml

Valid "encoding" settings:

- utf_8
- us_ascii

Valid "video_fast_update" settings:

- INFO
- DISABLE

Valid "http_caching", "schema_validation", "clear_db", "dtmf_start_time", "adv_digit_pattern", "cert_verify_peer", and "cert_verify_host" settings:

- yes
- no

Valid "bandwidth_modifier" settings (in kbps):

- None, 48, 64, 128, 256, 400, 512, 800, 1024, 2048, 4096

Valid "dtmf_detect_mode" settings:

- RFC2833
- IN-BAND

Valid "default_amr_alignment" settings:

- BANDWIDTH_EFFICIENT
- OCTET_ALIGNED

Valid "dns_cache_timeout" settings (in seconds):

- 0 means no cache
- -1 means cache forever

CPA (cpa) configuration defines how CPA operates. For instance, the time required before "no answer" is declared. In a MSML script, the "cfgname" attribute is set on the <cpa> element to specify the "config1" configuration as follows.

```
<cpa cfgname="config1"/>
```

Continuous No Signal (cnosig) is the maximum time of silence, with no signal, allowed immediately after cadence detection begins. If exceeded, a "no ringback" MSML event is generated by the media server.

No Answer (no_answer) is the length of time to wait after first ringback before deciding that the call is not answered.

PAMD Fail Time (pamd_failtime) is the maximum time to wait for positive answering machine detection or positive voice detection after a cadence break.

Method	Request Payload	Response Payload
JSON	<pre>{ "http_caching" : "yes", "cpa": [{ "config2": { "cnosig": 40000, "no answer": 30000, "pamd_failtime": 4000 } }] }</pre>	<pre>{ "version": "1.1", "http_caching": "yes", "schema_validation": "no", "adaptor_port": "32868", "storage_directory": "/var/lib/xms/media/en US", "content_type": "xml", "encoding": "utf_8", "clear_db": "yes", "dtmf_start_time": "no", "adv_digit_pattern": "no", "video fast update": "INFO", "video_bandwidth": "512", "conf_agc_default": "no", "default_amr_alignment": "BANDWIDTH EFFICIENT", "dtmf_detect_mode": "RFC2833", "dns_cache_timeout": "60", "cert_verify_peer": "no", "cert_verify_host": "no", "cpa": [{ "config2": { "cnosig": 40000, "no_answer": 30000, "pamd_failtime": 4000 } }] }</pre>

/media

Resource URI

/media

HTTP GET

Retrieves a list of media files and directories.

GET /media

Method	Response Payload
JSON	<pre>{ "locale": "en-US", "name": "", "type": "dir", "uri": "/media", "children": [{ "name": "verification", "type": "dir", "uri": "/media/verification", "children": [{ "name": "play_menu.jpeg", "type": "file", "uri": "/media/verification/play_menu.jpeg" }, { "name": "greeting.jpeg", "type": "file", </pre>

Method	Response Payload
	<pre> "uri": "/media/verification/greeting.jpeg" }, { "name": "record intro.wav", "type": "file", "uri": "/media/verification/record intro.wav" }, { "name": "main_menu.jpeg", "type": "file", "uri": "/media/verification/main_menu.jpeg" }, { "name": "greeting.wav", "type": "file", "uri": "/media/verification/greeting.wav" }, { "name": "record_intro.jpeg", "type": "file", "uri": "/media/verification/record intro.jpeg" }, { "name": "play_menu.wav", "type": "file", "uri": "/media/verification/play_menu.wav" }, { "name": "verification intro.wav", "type": "file", "uri": "/media/verification/verification_intro.wav" }, { "name": "main_menu.wav", "type": "file", "uri": "/media/verification/main_menu.wav" }] }, { "name": "vxml", "type": "dir", "uri": "/media/vxml", "children": [{ "name": "recorded", "type": "dir", "uri": "/media/vxml/recorded", "children": [] }, { "name": "generic", "type": "dir", "uri": "/media/vxml/generic", "children": [{ "name": "audio", "type": "dir", "uri": "/media/vxml/generic/audio", "children": [{ "name": "beep.wav", "type": "file", "uri": "/media/vxml/generic/audio/beep.wav" }, { "name": "maxspeechtimeout.wav", </pre>

Method	Response Payload
	<pre> "type": "file", "uri": "/media/vxml/generic/audio/maxspeechtimeout.wav" }, { "name": "calltimeout.wav", "type": "file", "uri": "/media/vxml/generic/audio/calltimeout.wav" }, { "name": "genericerror.wav", "type": "file", "uri": "/media/vxml/generic/audio/genericerror.wav" }, { "name": "nomatch.wav", "type": "file", "uri": "/media/vxml/generic/audio/nomatch.wav" }, { "name": "semantic.wav", "type": "file", "uri": "/media/vxml/generic/audio/semantic.wav" }, { "name": "transferaudio.wav", "type": "file", "uri": "/media/vxml/generic/audio/transferaudio.wav" }, { "name": "help.wav", "type": "file", "uri": "/media/vxml/generic/audio/help.wav" }, { "name": "badfetch.wav", "type": "file", "uri": "/media/vxml/generic/audio/badfetch.wav" }, { "name": "exit.wav", "type": "file", "uri": "/media/vxml/generic/audio/exit.wav" }] } }] }, { "name": "black.jpeg", "type": "file", "uri": "/media/black.jpeg" }] } </pre>

HTTP POST

Creates and replaces a media file.

Content-Type: "audio/wav" or "video/mp4" or "image/jpeg"

POST /media/<path/to/file>

HTTP DELETE

Deletes a media file.

```
DELETE /media/<path/to/file>
```

/tones

The tones API is used to configure custom tone detection templates.

A tone template may define either a single tone or dual tones, which may be either continuous or cadenced. Dual tones with frequency components closer than approximately 63Hz cannot be detected, for these cases a single tone definition should be used. A maximum of 20 tone templates may be defined.

Parameters

- **freq1**, frequency 1 in Hz (300Hz to 3.5kHz).
- **fq1dev**, frequency 1 deviation in Hz.
- **freq2**, frequency 2 in Hz (300Hz to 3.5kHz). Set to 0 to define a single tone.
- **fq2dev**, frequency 2 deviation in Hz. Dual tone only.
- **ontime**, tone-on time in milliseconds (minimum 40ms). Set to 0 to define a continuous tone.
- **ontdev**, tone-on time deviation in milliseconds. Cadenced only.
- **offtime**, tone-off time in milliseconds (minimum 40ms). Cadenced only.
- **offtdev**, tone-off time deviation in milliseconds. Cadenced only.

Resource URI

```
/tones
```

HTTP GET

Retrieves all tone templates.

```
GET /tones
```

Method	Response Payload
JSON	<pre>{ "tones" : [{ "1kHz" : { "freq1" : 1000, "fq1dev" : 20, "freq2" : 0, "fq2dev" : 0, "ontime" : 0, "ontdev" : 0, "offtime" : 0, "offtdev" : 0 } }, { "busy" : { "freq1" : 480, "fq1dev" : 40, "freq2" : 620, "fq2dev" : 40, "ontime" : 500, "ontdev" : 50, "offtime" : 500, </pre>

Method	Response Payload
	<pre> "offtdev" : 50 } }, "cpa_tones": [{ "busy1": { "freq1": 480, "fq1dev": 30, "freq2": 620, "fq2dev": 30, "twinfreq": 0, "twindev": 0, "ontime": 500, "ontdev": 150, "offtime": 500, "offtdev": 150, "repcnt": 2 } }, { "busy2": { "freq1": 480, "fq1dev": 30, "freq2": 620, "fq2dev": 30, "twinfreq": 0, "twindev": 0, "ontime": 250, "ontdev": 150, "offtime": 250, "offtdev": 150, "repcnt": 2 } }, { "dialtone_international": { "freq1": 340, "fq1dev": 40, "freq2": 440, "fq2dev": 40, "twinfreq": 390, "twindev": 90, "ontime": 1000, "ontdev": 0, "offtime": 0, "offtdev": 0, "repcnt": 1 } }, { "dialtone local": { "freq1": 340, "fq1dev": 40, "freq2": 440, "fq2dev": 40, "twinfreq": 390, "twindev": 90, "ontime": 100, "ontdev": 0, "offtime": 0, "offtdev": 0, "repcnt": 1 } }, { "fax1": { </pre>

Method	Response Payload
	<pre> "freq1": 1100, "fq1dev": 50, "freq2": 0, "fq2dev": 0, "twinfreq": 0, "twindev": 0, "ontime": 350, "ontdev": 250, "offtime": 0, "offtdev": 0, "repcnt": 1 } }, { "fax2": { "freq1": 2150, "fq1dev": 150, "freq2": 0, "fq2dev": 0, "twinfreq": 0, "twindev": 0, "ontime": 100, "ontdev": 0, "offtime": 0, "offtdev": 0, "repcnt": 1 } }, { "ringback1": { "freq1": 440, "fq1dev": 50, "freq2": 480, "fq2dev": 50, "twinfreq": 450, "twindev": 100, "ontime": 2000, "ontdev": 200, "offtime": 4000, "offtdev": 200, "repcnt": 1 } }, { "ringback2:seg1": { "freq1": 450, "fq1dev": 100, "freq2": 450, "fq2dev": 100, "twinfreq": 450, "twindev": 100, "ontime": 600, "ontdev": 400, "offtime": 600, "offtdev": 400, "repcnt": 0 } }, { "ringback2:seg2": { "freq1": 450, "fq1dev": 100, "freq2": 450, "fq2dev": 100, "twinfreq": 450, "twindev": 100, "ontime": 600, </pre>

Method	Response Payload
	<pre> "ontdev": 400, "offtime": 3500, "offtdev": 2500, "repcnt": 1 } }, { "sit_no_circuit:seg1": { "freq1": 985, "fq1dev": 35, "freq2": 0, "fq2dev": 0, "twinfreq": 0, "twindev": 0, "ontime": 385, "ontdev": 65, "offtime": 0, "offtdev": 0, "repcnt": 0 } }, { "sit no circuit:seg2": { "freq1": 1425, "fq1dev": 25, "freq2": 0, "fq2dev": 0, "twinfreq": 0, "twindev": 0, "ontime": 385, "ontdev": 65, "offtime": 0, "offtdev": 0, "repcnt": 0 } }, { "sit_no_circuit:seg3": { "freq1": 1795, "fq1dev": 55, "freq2": 0, "fq2dev": 0, "twinfreq": 0, "twindev": 0, "ontime": 0, "ontdev": 0, "offtime": 0, "offtdev": 0, "repcnt": 1 } }, { "sit_operator_intercept:seg1": { "freq1": 915, "fq1dev": 40, "freq2": 0, "fq2dev": 0, "twinfreq": 0, "twindev": 0, "ontime": 225, "ontdev": 75, "offtime": 0, "offtdev": 0, "repcnt": 0 } }, { </pre>

Method	Response Payload
	<pre> "sit_operator_intercept:seg2": { "freq1": 1370, "fq1dev": 60, "freq2": 0, "fq2dev": 0, "twinfreq": 0, "twindev": 0, "ontime": 225, "ontdev": 75, "offtime": 0, "offtdev": 0, "repcnt": 0 }, { "sit_operator_intercept:seg3": { "freq1": 1795, "fq1dev": 55, "freq2": 0, "fq2dev": 0, "twinfreq": 0, "twindev": 0, "ontime": 0, "ontdev": 0, "offtime": 0, "offtdev": 0, "repcnt": 1 } }, { "sit_reorder:seg1": { "freq1": 915, "fq1dev": 40, "freq2": 0, "fq2dev": 0, "twinfreq": 0, "twindev": 0, "ontime": 225, "ontdev": 75, "offtime": 0, "offtdev": 0, "repcnt": 0 } }, { "sit_reorder:seg2": { "freq1": 1425, "fq1dev": 25, "freq2": 0, "fq2dev": 0, "twinfreq": 0, "twindev": 0, "ontime": 385, "ontdev": 65, "offtime": 0, "offtdev": 0, "repcnt": 0 } }, { "sit_reorder:seg3": { "freq1": 1795, "fq1dev": 55, "freq2": 0, "fq2dev": 0, "twinfreq": 0, "twindev": 0, </pre>

Method	Response Payload
	<pre> "ontime": 0, "ontdev": 0, "offtime": 0, "offtdev": 0, "repcnt": 1 } }, { "sit_vacant_circuit:seg1": { "freq1": 985, "fq1dev": 35, "freq2": 0, "fq2dev": 0, "twinfreq": 0, "twindev": 0, "ontime": 385, "ontdev": 65, "offtime": 0, "offtdev": 0, "repcnt": 0 } }, { "sit_vacant_circuit:seg2": { "freq1": 1370, "fq1dev": 60, "freq2": 0, "fq2dev": 0, "twinfreq": 0, "twindev": 0, "ontime": 225, "ontdev": 75, "offtime": 0, "offtdev": 0, "repcnt": 0 } }, { "sit_vacant_circuit:seg3": { "freq1": 1795, "fq1dev": 55, "freq2": 0, "fq2dev": 0, "twinfreq": 0, "twindev": 0, "ontime": 0, "ontdev": 0, "offtime": 0, "offtdev": 0, "repcnt": 1 } }] }</pre>

HTTP PUT

Updates all tone templates.

PUT /tones

Method	Request Payload	Response Payload
JSON	<pre>{ "tones" : [{ "1kHz" : { "freq1" : 1000, "fq1dev" : 20, "freq2" : 0, "fq2dev" : 0, "ontime" : 0, "ontdev" : 0, "offtime" : 0, "offtdev" : 0 } }, { "busy" : { "freq1" : 480, "fq1dev" : 40, "freq2" : 620, "fq2dev" : 40, "ontime" : 500, "ontdev" : 50, "offtime" : 500, "offtdev" : 50 } }, { "congestion" : { "freq1" : 480, "fq1dev" : 40, "freq2" : 620, "fq2dev" : 40, "ontime" : 200, "ontdev" : 50, "offtime" : 300, "offtdev" : 50 } }] }</pre>	<pre>{ "tones" : [{ "1kHz" : { "freq1" : 1000, "fq1dev" : 20, "freq2" : 0, "fq2dev" : 0, "ontime" : 0, "ontdev" : 0, "offtime" : 0, "offtdev" : 0 } }, { "busy" : { "freq1" : 480, "fq1dev" : 40, "freq2" : 620, "fq2dev" : 40, "ontime" : 500, "ontdev" : 50, "offtime" : 500, "offtdev" : 50 } }, { "congestion" : { "freq1" : 480, "fq1dev" : 40, "freq2" : 620, "fq2dev" : 40, "ontime" : 200, "ontdev" : 50, "offtime" : 300, "offtdev" : 50 } }] }</pre>

/network

Resource URI

/network

Resources

Resource	Description
interface	Network interface configuration resource
dns	Network DNS configuration resource

HTTP GET

Retrieves all available system resources.

GET /network

Method	Response Payload
JSON	<pre>{ "resources" : [{ "uri" : "\network\interface" }, { "uri" : "\network\dns" }] }</pre>

/network/interface

Resource URI

/network/interface

HTTP GET

Retrieves all network interfaces on the system.

GET /network/interface

Method	Response Payload
JSON	<pre>{ "interfaces" : [{ "ifname" : "lo", "uri" : "\network\interface\lo" }, { "ifname" : "eth0", "uri" : "\network\interface\eth0" }, { "ifname" : "eth0:0", "uri" : "\network\interface\eth0:0" }], }</pre>

Single Instance

Retrieves information for a single network interface.

GET /network/interface/eth0

Method	Response Payload
JSON	<pre>{ "if_name" : "eth0" "ipv4_addr" : "10.20.129.12", "ipv4_mask" : "255.255.255.0", "gateway" : "10.20.129.250" "ipv6_addr" : "fe80::20c:29ff:feb6:1805", "ipv6_prfx" : "64", "ipv6gateway" : "fe80::20c:29ff:feb6:0", "active" : "yes" }</pre>

HTTP PUT

Configures a single network interface.

PUT /network/interface/eth0

Method	Request Payload	Response Payload
JSON	<pre>{ "if_name" : "eth0" "ipv4_addr" : "10.20.129.13", "ipv4_mask" : "255.255.255.1", "gateway" : "10.20.129.251" "ipv6_addr" : "fe80::20c:29ff:feb6:1815", "ipv6_prfx" : "64", "ipv6gateway" : "fe80::20c:29ff:feb6:9", }</pre>	<pre>{ "if_name" : "eth0" "mac" : "00:0c:29:60:18:02" "ipv4_addr" : "10.20.129.13", "ipv4_mask" : "255.255.255.1", "method" : "static", "gateway" : "10.20.129.251" "ipv6_addr" : "fe80::20c:29ff:feb6:1815", "ipv6_prfx" : "64", "ipv6gateway" : "fe80::20c:29ff:feb6:9", "active" : "yes" }</pre>

/network/dns

Resource URI

/network/dns

HTTP GET

Retrieves the DNS information on the system.

GET /network/dns

Method	Response Payload
JSON	<pre>{ "hostname": "xms.localdomain", "search": "dialogic.com", "nameserver": [{ "addr": "10.20.106.1" }, { "addr": "10.20.106.2" }] }</pre>

HTTP PUT

Configures the DNS information on the system.

PUT /network/dns

Method	Request Payload
JSON	<pre>{ "hostname" : "ab.xyz.com", "search" : "xyz.com", "nameserver": [{ "addr": "192.168.23.1" }, { "addr": "192.168.23.2" }] }</pre>

/mrcpclient

Resource URI

/mrcpclient

Resources

Resource	Description
global	MRCP Client Global configuration resource
speechserver_sample	MRCP Client Speechserver_sample configuration resource
speechserver_speechserver1	MRCP Client Speechserver_speechserver1 configuration resource

HTTP GET

Retrieves all available MRCP Client resources.

GET /mrcpclient

Method	Response Payload
JSON	<pre>{ "resources": [{ "uri": "/mrcpclient/global" }, { "uri": "/mrcpclient/speechserver sample" }] }</pre>

HTTP PUT

Adds a new or delete an old MRCP Client resource (speechserver).

PUT /mrcpclient

Adds a New Resource

Method	Request Payload	Response Payload
JSON	<pre>{ "resources": [{ "uri": "/mrcpclient/global" }, { "uri": "/mrcpclient/speechserver_sample" }, { "uri": "/mrcpclient/speechserver_speechserver1" }] }</pre>	<pre>{ "resources": [{ "uri": "/mrcpclient/global" }, { "uri": "/mrcpclient/speechserver_sample" }, { "uri": "/mrcpclient/speechserver_speechserver1" }] }</pre>

Deletes an Old Resource

Method	Request Payload	Response Payload
JSON	<pre>{ "resources": [{ "uri": "/mrcpclient/global" }, { "uri": "/mrcpclient/speechserver speechserver1" }] }</pre>	<pre>{ "resources": [{ "uri": "/mrcpclient/global" }, { "uri": "/mrcpclient/speechserver speechserver1" }] }</pre>

/mrcpclient/global

Resource URI

/mrcpclient/global

HTTP GET

Retrieves the MRCP Client Global configuration.

GET /mrcpclient/global

Method	Response Payload
JSON	<pre>{ "clientaddress": "0.0.0.0", "keepaliveinterval": "10000", "keepalivecount": "3", "udpretransmittimer" : "100", "udpmaxretransmitcount" : "2", "serverrecoverydelay" : "5", "maxsessions": "100" }</pre>

HTTP PUT

Configures the MRCP Client Global resource.

PUT /mrpcclient/global

Method	Request Payload	Response Payload
JSON	<pre>{ "clientaddress": "10.20.110.80", "keepaliveinterval": "20000", "keepalivecount": "4", "maxsessions": "20" }</pre>	<pre>{ "clientaddress": "10.20.110.80", "keepaliveinterval": "20000", "keepalivecount": "4", "udpretransmittimer" : "100", "udpmaxretransmitcount" : "2", "serverrecoverydelay" : "5", "maxsessions": "20" }</pre>

/mrpcclient/speechserver_sample

Resource URI

/mrpcclient/speechserver_sample

HTTP GET

Retrieves the MRCP Client speechserver_sample configuration.

GET /mrpcclient/speechserver_sample

Method	Response Payload
JSON	<pre>{ "id": "sample", "protocol": "MRCP/2.0", "session": "SIP/2.0", "transport": "TCP", "address": "127.0.0.1", "port": "5060", "asr": "true", "tts": "false" }</pre>

HTTP PUT

Configures the MRCP Client speechserver_sample resource.

PUT /mrpcclient/speechserver_sample

Method	Request Payload	Response Payload
JSON	<pre>{ "transport": "UDP", "address": "127.0.0.1", "port": "5080", "asr": "false", "tts": "true" }</pre>	<pre>{ "id": "sample", "protocol": "MRCP/2.0", "session": "SIP/2.0", "transport": "UDP", "address": "127.0.0.1", "port": "5080", "asr": "false", "tts": "true" }</pre>

/mrcpclient/speechserver_speechserver1

Resource URI

/mrcpclient/speechserver_speechserver1

HTTP GET

Retrieves the MRCP Client speechserver_speechserver1 configuration.

GET /mrcpclient/speechserver_speechserver1

Method	Response Payload
JSON	<pre>{ "id": "speechserver1", "protocol": "MRCP/2.0", "session": "SIP/2.0", "transport": "TCP", "address": "127.0.0.1", "port": "5060", "asr": "true", "tts": "false" }</pre>

HTTP PUT

Configures the MRCP Client speechserver_speechserver1 resource.

PUT /mrcpclient/speechserver_speechserver1

Method	Request Payload	Response Payload
JSON	<pre>{ "transport": "UDP", "address": "127.0.0.1", "port": "5080", "asr": "false", "tts": "true" }</pre>	<pre>{ "id": "speechserver1", "protocol": "MRCP/2.0", "session": "SIP/2.0", "transport": "UDP", "address": "127.0.0.1", "port": "5080", "asr": "false", "tts": "true" }</pre>

/netann

Resource URI

/netann

Resources

Resource	Description
global	NETANN global configuration resource
conference	NETANN conference configuration resource

HTTP GET

Retrieves all available NETANN resources.

GET /netann

Method	Response Payload
JSON	<pre>{ "resources": [{ "uri": "/netann/global" }, { "uri": "/netann/conference" }] }</pre>

/netann/global

Resource URI

/netann/global

HTTP GET

Retrieves the NETANN global configuration.

GET /netann/global

Method	Response Payload
JSON	<pre>{ "media": "audiovideo" }</pre>

HTTP PUT

Configures the NETANN global resource.

PUT /netann/global

Method	Request Payload	Response Payload
JSON	<pre>{ "media": ["audiovideo" or "audio"] }</pre>	<pre>{ "media": ["audiovideo" or "audio"] }</pre>

/netann/conference

Resource URI

/netann/conference

HTTP GET

Retrieves the NETANN conference configuration.

GET /netann/conference

Method	Response Payload
JSON	<pre>{ "max_conf_parties": "500", "max_audio_conf": "1000", "max_video_conf": "100", "conf_video_regions": "0" }</pre>

HTTP PUT

Configures the NETANN conference resource.

PUT /netann/conference

Method	Request Payload	Response Payload
JSON	<pre>{ "max_conf_parties": ["1" to "500"], "max_audio_conf": ["0" to "1000"], "max video conf": ["0" to "100"], "conf video regions": ["0" to "9"] }</pre>	<pre>{ "max_conf_parties": ["1" to "500"], "max_audio_conf": ["0" to "1000"], "max video conf": ["0" to "100"], "conf video regions": ["0" to "9"] }</pre>

/resource

Resource URI

/resource

Resources

Resource	Description
active	The active resource meters
groups	The groups resource meters
licenses	The licenses resource meters

HTTP GET

Retrieves all available resource meters.

GET /resource

Method	Response Payload
JSON	<pre>{ "resources": [{ "uri": "/resource/active" }, { "uri": "/resource/groups" }, { "uri": "/resource/licenses" }] }</pre>

/resource/active

Resource URI

/resource/active

HTTP GET

Retrieves the active resource meters.

GET /resource/active

Method	Response Payload
JSON	<pre>{ "Signaling Sessions": "20" "RTP Sessions": "40" "Media Transactions": "30" "Conference Rooms": "4" "Conference Media Parties": "16" "ASR / TTS Sessions": "0" "Conference Parties": "16" }</pre>

/resource/groups

Resource URI

/resource/groups

HTTP GET

Retrieves the groups resource meters.

GET /resource/groups

Method	Response Payload
JSON	<pre>{ "name1": "12" "name2": "5" }</pre>

/resource/licenses

Resource URI

/resource/licenses

HTTP GET

Retrieves the licenses resource meters.

GET /resource/licenses

Method	Response Payload
JSON	<pre>{ "Advanced Video": "2,0,2,0.0" "Basic Audio": "2,0,2,0.0" "GSMAMR Audio": "2,0,2,0.0" "HD Voice": "2,0,2,0.0" "High Resolution Video": "2,0,2,0.0" "LBR Audio=": "2,0,2,0.0" "MRCP Speech Server": "2,0,2,0.0" "MSRP": "2,0,2,0.0" }</pre>

/snmp

Resource URI

/snmp

Resources

Resource	Description
trap-destinations	SNMP Trap Destinations Configuration Resource
v2c-communities	SNMP V2C Communities Configuration Resource
v3-users	SNMP V3 Users Configuration Resource
thresholds	SNMP Trap Thresholds Configuration Resource

HTTP GET

Retrieves all available snmp resources.

GET /snmp

Method	Response Payload
JSON	<pre>{ "resources": [{ "uri": "/snmp/trap-destinations" }, { "uri": "/snmp/v2c-communities" }, { "uri": "/snmp/v3-users" }, { "uri": "/snmp/thresholds" }] }</pre>

/snmp/trap-destinations

Resource URI

/snmp/trap-destinations

HTTP GET

Retrieves SNMP Trap Destinations resource.

GET /snmp/trap-destinations

Method	Response Payload
JSON	<pre>[{ "ip_proto": "UDP", "host": "192.168.1.77", "port": 1177, "version": "V3", "snmpv3_attributes": { "engine_id": "0x1234", "security_name": "myuser", "auth_proto": "MD5", "priv_proto": "DES", "sec_level": "AuthPriv", "auth_key": "myauthpass", "priv_key": "myencrpass", "access": "RW" } }, { "ip_proto": "UDP", "host": "192.168.1.77", "port": 1177, "version": "V2c", "snmpv2c_attributes": { "community_string": "public", "access": "RW" } },]</pre>

HTTP PUT

Configures SNMP Trap Destinations resource.

PUT /snmp/trap-destinations

Method	Request Payload	Response Payload
JSON	<pre>[{ "ip_proto" : "UDP", "host" : "192.168.1.77", "port" : 1177, "version" : "V3", "snmpv3 attributes" : { "engine_id" : "0x1234", "security_name" : "myuser", "auth proto" : "MD5", "priv proto" : "DES", "sec_level" : "AuthPriv", "auth_key" : "myauthpass", "priv_key" : "myencrpass", "access" : "RW" } }, { "ip_proto" : "UDP", "host" : "192.168.1.77", "port" : 1177, "version" : "V2c", "snmpv2c attributes" : { "community string" : "public", "access" : "RW" } },]</pre>	<pre>[{ "ip_proto" : "UDP", "host" : "192.168.1.77", "port" : 1177, "version" : "V3", "snmpv3 attributes" : { "engine_id" : "0x1234", "security_name" : "myuser", "auth proto" : "MD5", "priv proto" : "DES", "sec_level" : "AuthPriv", "auth_key" : "myauthpass", "priv_key" : "myencrpass", "access" : "RW" } }, { "ip_proto" : "UDP", "host" : "192.168.1.77", "port" : 1177, "version" : "V2c", "snmpv2c attributes" : { "community string" : "public", "access" : "RW" } },]</pre>

/snmp/v2c-communities

Resource URI

/snmp/v2c-communities

HTTP GET

Retrieves SNMP v2c communities resource.

GET /snmp/v2c-communities

Method	Response Payload
JSON	<pre>[{ "community_string" : "Craftsperson", "access" : "RO" }, { "community_string" : "Administrator", "access" : "RW" }]</pre>

HTTP PUT

Configures SNMP v2c communities resource.

PUT /snmp/v2c-communities

Method	Request Payload	Response Payload
JSON	<pre>[{ "community_string" : "Craftsperson", "access" : "RO" }, { "community_string" : "Administrator", "access" : "RW" }]</pre>	<pre>[{ "community_string" : "Craftsperson", "access" : "RO" }, { "community_string" : "Administrator", "access" : "RW" }]</pre>

/snmp/v3-users

Resource URI

/snmp/v3-users

HTTP GET

Retrieves SNMP v3 users resource.

GET /snmp/v3-users

Method	Response Payload
JSON	<pre>[{ "engine_id" : "", "security_name" : "Administrator", "auth_proto" : "SHA", "priv_proto" : "DES", "sec_level" : "AuthPriv", "auth_key" : "CharlieChang", "priv_key" : "ChristyWang", "access" : "RW" }, { "engine id" : "", "security_name" : "Craftsperson", "auth_proto" : "MD5", "priv_proto" : "DES", "sec_level" : "AuthPriv", "auth_key" : "Craftsperson", "priv_key" : "Craftsperson", "access" : "RW" }]</pre>

HTTP PUT

Configures SNMP v3 users resource.

PUT /snmp/v3-users

Method	Request Payload	Response Payload
JSON	<pre>[{ "engine_id" : "", "security_name" : "Administrator", "auth_proto" : "SHA", "priv_proto" : "DES", "sec_level" : "AuthPriv", "auth_key" : "CharlieChang", "priv_key" : "ChristyWang", "access" : "RW" }, { "engine_id" : "", "security_name" : "Craftsperson", "auth_proto" : "MD5", "priv_proto" : "DES", "sec_level" : "AuthPriv", "auth_key" : "Craftsperson", "priv_key" : "Craftsperson", "access" : "RW" }]</pre>	<pre>[{ "engine_id" : "", "security_name" : "Administrator", "auth_proto" : "SHA", "priv_proto" : "DES", "sec_level" : "AuthPriv", "auth_key" : "CharlieChang", "priv_key" : "ChristyWang", "access" : "RW" }, { "engine_id" : "", "security_name" : "Craftsperson", "auth_proto" : "MD5", "priv_proto" : "DES", "sec_level" : "AuthPriv", "auth_key" : "Craftsperson", "priv_key" : "Craftsperson", "access" : "RW" }]</pre>

/snmp/thresholds

Resource URI

/snmp/thresholds

HTTP GET

Retrieves SNMP Trap Thresholds resource.

GET /snmp/thresholds

Method	Response Payload
JSON	<pre>{ "amraudio" : 100, "basicaudio" : 100, "hdaudio" : 70, "lbraudio" : 75, "mrpcspeech" : 85, "basicvideo" : 100, "hiresvideo" : 80 }</pre>

HTTP PUT

Configures SNMP Trap Thresholds resource.

PUT /snmp/thresholds

Method	Request Payload	Response Payload
JSON	<pre>{ "amraudio" : 100, "basicaudio" : 100, "hdaudio" : 70, "lbraudio" : 75, "mr cpspeech" : 85, "basicvideo" : 100, "hiresvideo" : 80 }</pre>	<pre>{ "amraudio" : 100, "basicaudio" : 100, "hdaudio" : 70, "lbraudio" : 75, "mr cpspeech" : 85, "basicvideo" : 100, "hiresvideo" : 80 }</pre>

/vxml

Resource URI

/vxml

Resources

Resource	Description
interpreter	VXML Interpreter configuration resource

HTTP GET

Retrieves all available VXML resources.

GET /vxml

Method	Response Payload
JSON	<pre>{ "resources": [{ "uri": "/vxml/vxmlinterpreter" }] }</pre>

/vxml/vxmlinterpreter

Resource URI

/vxml/vxmlinterpreter

HTTP GET

Retrieves the VXML Interpreter configuration.

GET /vxml/vxmlinterpreter

Method	Response Payload
JSON	<pre>{ "AllowCallTransfer": "true", "DefaultCompleteTimeout": "0.25s", "DefaultGrammarLocale": "en-US", "DefaultIncompleteTimeout": "0.75s", "DefaultInitialURI": "%VXMLROOT%/www/vxml/index.vxml", "DefaultInterDigitTimeout": "3s", "DefaultTimeout": "3.4s", "DefaultTTSLang": "en-US", "NumChannels": "5", "SystemLogLevel": "1", "VXMLAppLogsEnabled": "true", "StaticContentDir": "/var/lib/xms/vxml/www", "WebServerLocalIpAddress": "127.0.0.1", "WebServerListenPort": "9002", "WebServerUsername": "", "WebServerPassword": "" }</pre>

HTTP PUT

Configures the VXML Interpreter resource.

PUT /vxml/vxmlinterpreter

Method	Request Payload	Response Payload
JSON	<pre>{ "AllowCallTransfer": "false", "SystemLogLevel": "5", }</pre>	<pre>{ "AllowCallTransfer": "false", "DefaultCompleteTimeout": "0.25s", "DefaultGrammarLocale": "en-US", "DefaultIncompleteTimeout": "0.75s", "DefaultInitialURI": "%VXMLROOT%/www/vxml/index.vxml", "DefaultInterDigitTimeout": "3s", "DefaultTimeout": "3.4s", "DefaultTTSLang": "en-US", "NumChannels": "5", "SystemLogLevel": "5", "VXMLAppLogsEnabled": "true", "StaticContentDir": "/var/lib/xms/vxml/www", "WebServerLocalIpAddress": "127.0.0.1", "WebServerListenPort": "9002", "WebServerUsername": "", "WebServerPassword": "" }</pre>

/xmsrest

Resource URI

/xmsrest

Resources

Resource	Description
general	RESTful call and media API general configuration resource
trusted	RESTful call and media API trusted application configuration resource

HTTP GET

Retrieves all available XMSREST resources.

GET /xmsrest

Method	Response Payload
JSON	<pre>{ "resources": [{ "uri": "/xmsrest/general" }, { "uri": "/xmsrest/trusted" }] }</pre>

/xmsrest/general

Resource URI

/xmsrest/general

HTTP GET

Retrieves the XMSREST general configuration.

GET /xmsrest/general

Method	Response Payload
JSON	<pre>{ "port": "81" "enable_restful_ipv6": "no" }</pre>

HTTP PUT

Configures the XMSREST general resource.

PUT /xmsrest/general

Method	Request Payload	Response Payload
JSON	<pre>{ "port": "8181" "enable restful ipv6": "yes" }</pre>	<pre>{ "port": "8181" "enable restful ipv6": "yes" }</pre>

/xmsrest/trusted

Resource URI

/xmsrest/trusted

HTTP GET

Retrieves all trusted apps.

GET /xmsrest/trusted

Method	Response Payload
JSON	<pre>{ "app": "enable", "app2": "enable" }</pre>

HTTP PUT

Adds, deletes, or modifies trusted apps.

PUT /xmsrest/trusted

Method	Request Payload	Response Payload
JSON	<pre>{ "app3": "enable", "app2": "disable" }</pre>	<pre>{ "app3": "enable", "app2": "disable" }</pre>

/msrp

Resource URI

/msrp

Resources

Resource	Description
global	MSRP Global configuration resource

HTTP GET

Retrieves all available MSRP resources.

GET /msrp

Method	Response Payload
JSON	<pre>{ "resources": [{ "uri": "/msrp/global" }] }</pre>

/msrp/global

Resource URI

/msrp/global

HTTP GET

Retrieves the MSRP Global configuration.

GET /msrp/global

Method	Response Payload
JSON	<pre>{ "msrpaddress" : "0.0.0.0", "msrpport" : "2855", "tcpenabled" : "true", "tlsenabled" : "false", "chunksize" : "2048", "responsedelay" : "30", "maxsessions" : "100", "numberofthreads" : "1", "connectiontimeout" : "30", "successreport" : "no", "failurereport" : "yes", "filepath" : "/var/lib/xms/media/en-US", "absolutePaths" : "no" }</pre>

HTTP PUT

Configures the MSRP Global resource.

PUT /msrp/global

Method	Request Payload	Response Payload
JSON	<pre>{ "msrpaddress" : "10.40.2.106", "msrpport" : "2856", "tcpenabled" : "false", "tlsenabled" : "true", "chunksize" : "1024", "responsedelay" : "50", "maxsessions" : "200", "connectiontimeout" : "40", "successreport" : "yes", "failurereport" : "partial", "filepath" : "/var/lib/xms/media/sp-SP", "absolutePaths" : "yes" }</pre>	<pre>{ "msrpaddress" : "10.40.2.106", "msrpport" : "2856", "tcpenabled" : "false", "tlsenabled" : "true", "chunksize" : "1024", "responsedelay" : "50", "maxsessions" : "200", "connectiontimeout" : "40", "successreport" : "yes", "failurereport" : "partial", "filepath" : "/var/lib/xms/media/sp-SP", "absolutePaths" : "yes" }</pre>